




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04B 3/54		A1	(11) International Publication Number: WO 95/29537
			(43) International Publication Date: 2 November 1995 (02.11.95)
(21) International Application Number: PCT/GB95/00894		(81) Designated States: AM, AT, AU, BB, BG, BR, BY, CA, CH, CN, CZ, DE, DK, EE, ES, FI, GB, GE, HU, IS, JP, KE, KG, KP, KR, KZ, LK, LR, LT, LU, LV, MD, MG, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, TJ, TM, TT, UA, UG, US, UZ, VN, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG), ARIPO patent (KE, MW, SD, SZ, UG). Published With international search report.	
(22) International Filing Date: 20 April 1995 (20.04.95)			
(30) Priority Data: 9407934.0 21 April 1994 (21.04.94) GB			
(71) Applicant (for all designated States except US): NORWEB PLC [GB/GB]; Talbot Road, Manchester M16 0HQ (GB).			
(72) Inventor; and (75) Inventor/Applicant (for US only): BROWN, Paul, Anthony [GB/GB]; 30 Applerigg, Kendal, Cumbria LA9 6EA (GB).			
(74) Agents: HACKNEY, Nigel, J. et al.; Mewburn Ellis, York House, 23 Kingsway, London WC2B 6HP (GB).			

(54) Title: POWERLINE COMMUNICATIONS NETWORK EMPLOYING TDMA, FDMA AND/OR CDMA



(57) Abstract

Communications apparatus is disclosed which is adapted for use with a mains electricity transmission and/or distribution network, and includes signal transmission and/or reception means (232), and frequency conversion means (200-208) for converting the frequency of a signal transmitted or received by signal transmission and/or reception means to a frequency which facilitates improved propagation of the signal on the network. Preferably the signal transmission and/or reception means is adapted to operate according to a telephony standard which uses a relatively high carrier frequency (e.g. CT2), and the frequency conversion means is usable to convert a signal having a relatively high carrier frequency to a signal having a lower carrier frequency.

THIS PAGE BLANK (USPTO)

POWERLINE COMMUNICATIONS NETWORK EMPLOYING TDMA, FDMA AND/OR CDMA

This invention relates to a method of signal injection, transmission, interconnection (termination) and detection, and to a power transmission network, ie. a mains electricity distribution and/or transmission network, and a filter therefor. In particular it relates to the use of mains electricity networks and/or lines for telecommunications transmission (e.g. voice, data, image and/or video).

In the UK, it is conventional to describe a power network for 33kV and above as a "transmission network", and one for less than 33kV as a "distribution network". In this specification the term "electricity distribution and/or power transmission network" is normally used, but general references to power networks and to transmission of signals are to be construed as applying to all such networks.

20

Traditionally telecommunications signals have been transmitted on independent networks e.g. telephone lines. More recently, in order to simplify and increase efficiency of telecommunications services to domestic or industrial premises, there have been investigations into using existing electricity transmission and distribution networks to carry telecommunications services.

It has been known to utilise above ground (overhead) power lines for the transmission of additional control speech and data signals. However, with such transmissions, the frequency spectrum must be allocated for and restricted to

particular applications in order to avoid interference with other telecommunications services. In addition, the strength of signals which can be transmitted is limited since the amount of radiation produced by the transmission
5 is related to the strength of the signal and this radiation must be kept to a minimum.

Such transmission signals must therefore be of low power and confined within a specific frequency band allocated by
10 international agreement for such purposes, so this mechanism is unsuitable for large scale voice and/or data transmission where signals extend well into the radio spectrum (e.g. 150 kHz and above).

15 It has been known to use spread spectrum techniques to transmit data at carrier frequencies of between 6kHz and 148kHz on underground and overhead power networks. Again, in this allocated frequency band such transmissions suffer from low data rates and low traffic capacities due to
20 power line noise characteristics. Due to the limited spectrum available and high noise levels encountered wideband telecommunications signals cannot be sent.

Although papers such as that by J.R. Formby and R.N.
25 Adams, ("The mains network as a high frequency signalling medium", The Electricity Council, January 1970) suggested a communications potential for the low and medium voltage networks, no further work was undertaken. Even today, with the prospect of remote meter reading and selective
30 load control, solutions tend to employ techniques such as telephony and radio communications, thus avoiding the mains network where possible.

Ideas have been put forward but few have proceeded past the theoretical stage, due to the hostile environment presented by the mains network. The problems to overcome include electrical noise, (both constant background noise and transient spikes) and high attenuation of high frequency signals due to skin and proximity effects.

Messrs Formby and Adams suggested using frequencies in the range of 80 to 100 kHz. 100 kHz was recommended as a maximum because theory suggested that higher frequencies would suffer from excessive attenuation. Other papers recommend a maximum of 150 kHz due to the fact that radiated signals higher than 150 kHz would interfere with broadcast radio signals.

15

A further situation where power lines are also used for the transmission of speech and data signals is on the electricity wiring inside buildings. In such configurations the internal 240V mains wiring is used for the transmission of data, with appropriate filtering being provided to add and separate the data signals from the power signals. Additionally a filter, such as the Emlux filter described in European Patent Application 141673, may be provided to prevent data signals leaving the building and entering the power supply network external to the building. The Emlux filter described consists of a tuned ferrite ring which acts effectively as a band stop filter. In order to be effective the band stop filter must be of narrow bandwidth and therefore is not suitable for use with high speed data communications, since a large number of such band stop filters would be required.

30

A further problem with sending telecommunications signals on a mains power network lies in the determination of a suitable technique or protocol for the transmission of those signals. As power networks are typically "trunk and branch multipoint" and/or "point to multipoint" networks there may be many different propagation paths and reflection points as a signal is transmitted along the network. This results in what is known as "delay spread" of the signal, that is the signal becomes spread out in time as it takes different propagation paths through the network. A typical delay spread may be around 5µs, and this must be taken into account when determining the data transmission rate.

The present invention aims to provide a transmission network which alleviates some or all of the above problems.

Accordingly, in a first aspect, the present invention provides an electricity distribution and/or power transmission network at least part of which is external to a building, the network including input means for the input onto the network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications signal from the network, said signal being transmissible along said external part of the network, wherein the network is adapted to transmit said signal using frequency, time and/or code division multiplexing techniques.

A wide range of different transmission techniques are

available for use with electricity power line communication each using various modulation methods including frequency, time and code division multiplexing.

It has been determined that the spread spectrum method

- 5 offers inherent security and good interference rejection characteristics. These properties are achieved using a large bandwidth and hence requires the design of a specific filter.

- 10 Modulation methods include amplitude, frequency, phase; single, double and vestigial sideband, pulse position, width and amplitude; frequency shift keying (FSK), Gaussian filtered FSK (GFSK), Gaussian minimum shift keying (GMSK), Quaternary phase shift keying (QPSK),
15 Orthogonal quaternary phase shift keying (OQPSK), Quadrature amplitude modulation (QAM), $\pi/4$ QPSK etc.

- A large number of standard cordless, mobile and cellular radio phone communication techniques may be suitable for
20 effecting signal transmission over a conditioned network.

- Preferably, the network is adapted to transmit said signal using one or more of the following cordless telephony techniques and/or standards: CTO, CT1 and CT2, AMPS, DECT
25 (Digital European Cordless Telephone Standard), IS-54, IS-95, GSM, Q-CDMA, R-CDMA, UD-PCS, PHS, PACS, TACS, ENTACS, NMT450, NMT900, C-450, RTMS, Radicom 2000, NTJ, JTACS & NTACS, DCS 1800, etc.

- 30 One particularly favourable telecommunications standard has been found to be the CT2 standard. However in normal use, CT2 equipment transmits and receives at a radio

frequency of around 866MHz. Accordingly, the network may include frequency conversion means for down converting the frequency of the signal to a frequency more suited for propagation on the network.

5

CT2 is a digital transmission standard and applying such a standard permits the signals to be frequency translated and regenerated at requisite points on the network thus extending the services to any or all sections of a network
10 irrespective of the overall attenuation offered by the network end to end.

One possible problem with using the CT2 standard is that the CT2 signal is prone to interference by noise. One way
15 round this problem is to use a different standard, namely the CDMA (Code Division Multiple Access) spread spectrum transmission techniques.

With CDMA, the signal is spread across the frequency
20 spectrum and therefore interference at any particular frequency does not necessarily effect the effectiveness of the data transmission included in the signal.

Furthermore, as the signal is spread across the spectrum then less power is needed to transmit the signal.

25

Advantageously, the present invention may make further use of this property of CDMA transmission. Accordingly, signals of a relatively narrow bandwidth may be superimposed over the relatively broad bandwidth CDMA
30 signal. The narrow bandwidth signal(s) will interfere with the CDMA signal at the particular frequency of the narrow bandwidth signal, but the CDMA signal will remain

undisturbed in other parts of its frequency range. Thus deliberate "interference" can be added to the CDMA signal. This could be used for, for example, transmitting narrow bandwidth data signals on top of a relatively broad
5 bandwidth telephony signal.

The term "carrier frequency" refers to the unmodulated frequency of the carrier signal, and not to the frequency of the telecommunications signal once modulated.

10

On, for example, a 415V network the carrier frequency may preferably be between 1-10MHz, and on, eg., a 11kV network may be between e.g. 1-20MHz, or possibly 5-60MHz. However the frequency may be up to 100's of MHz depending on the
15 network and the application. For example, over short distances (10-20m) a frequency range of e.g. 1-600MHz or 1-800MHz may be used.

The power network may include one or more phases.
20 Preferably the network is a polyphase network including e.g. any one or more of 2, 3, 4, 5, 6, 7 etc phases. Different sections of the network may include different numbers of phases.

25 The network may typically be a trunk and branch multipoint (or multipoint to point) electricity distribution and/or power transmission network.

30 Preferably the network is unbalanced i.e. provides unbalanced transmission characteristics. The cable(s) of the network may be screened or clad e.g. with a suitable metal material, which enables the cable to behave as a

pseudo-coaxial element to provide an unbalanced transmission network at the transmission frequency of the present invention.

- 5 Preferably the transmission network is external to any building or premises such as an office or house. Inside such buildings, transmission distances are typically short and therefore attenuation losses relatively unimportant.
- 10 Preferably the power network is a major (e.g. overground and/or underground) power network including e.g. any or all of 132kV, 33kV, 11kV, 415V and 240V sections. The voice and data signals may be transmitted over any or all of the sections of the power network by suitable
- 15 detection, amplification and/or regeneration and reintroduction as and when necessary.

- In a preferred embodiment, full duplex facilities are provided by utilising, for example, frequency (FDD), time
- 20 (TDD) and/or code division multiplexing and/or multiple access (CDMA) techniques, i.e. signals may be transmitted and/or received in all directions simultaneously.

- And/or*
- 25 A network according to the present invention may be used for many speech and/or data transmission purposes, such as remote reading of electricity meters, remote banking and shopping, energy management systems, telephony (voice), switched telephony, security systems and/or interactive data services, multimedia services and television.

30

According to a further aspect, the present invention provides communications apparatus adapted for use with a

mains electricity transmission and/or distribution network, including signal transmission and/or reception means, and frequency conversion means for converting the frequency of a signal transmitted or received by signal transmission and/or reception means to a frequency which facilitates improved propagation of the signal on the network.

Preferably, the signal transmission and/or reception means is adapted to operate according to a telephony standard which uses a relatively high carrier frequency (e.g. 500MHz-1GHz), and said frequency conversion means is usable to convert a signal having a relatively high carrier frequency to a signal having a lower carrier frequency (e.g. 1-60MHz).

In a preferred embodiment, the signal transmission and/or reception means is adapted to operate according to the CT2 or CDMA standards. Preferably the frequency conversion means is usable to convert the carrier frequency of the signal to between 1 and 20MHz.

Typically, the signal transmission and/or reception means may comprise telephony equipment e.g. a telephone or fax machine.

According to a further aspect, the present invention provides a method of signal transmission including input of a telecommunications signal having a carrier frequency of greater than approximately 1MHz onto an electricity power distribution and/or transmission network at least part of which is external to a building and subsequent

reception of the signal, said signal being transmitted along said external part of the network, wherein said signal is transmitted using frequency, time and/or code division multiplexing techniques.

5

- In a further aspect, the present invention provides a communications apparatus (known hereinafter as a "network conditioning unit") for use with a network according to the first aspect of the present invention. The network
- 10 conditioning unit includes a low pass filter portion or portions for filtering out the low frequency high amplitude mains power signal i.e. separating it from the telecommunications signal(s) and allowing it to pass through the conditioning unit. The unit also includes a
- 15 high pass coupling element for input and removal of telecommunications signals from the network and, preferably, a terminating element of similar impedance to the characteristic impedance of the network at that point.
- 20 The use of such a unit ensures that the high frequency telecommunications signals do not contaminate the internal low voltage wiring present inside a premises, and/or that noise sources from the internal low voltage premises wiring do not contaminate or corrupt the high frequency
- 25 telecommunications signals being transmitted over the external electricity transmission and/or distribution network.

- Preferably, the variable electrical loading effects (i.e.
- 30 the load impedances) of all items which are coupled onto the network from time to time and which utilise electrical energy (i.e. the electrical loads) are isolated from the

communications signals by the action of low pass filter element(s) of the conditioning unit(s).

Preferably an electrical filter is used at the interface
5 between the external distribution network and the internal network of the premises, e.g. a house, of a user to ensure that the two signals are separated. Such a filter should have minimal effect on the normal domestic electricity supply.

10

The filter element of the present invention, which aims to reduce telecommunications signals entering the internal network of a users premises, preferably has no more than 1
15 volt dropped across it whilst supplying a 100amp load from a 240v, 50HZ, single phase source.

Preferably the network conditioning unit provides impedance matching between reception/transmission devices and the power network. Additionally the network
20 conditioning unit may carry full load or fault current at power frequencies whilst still carrying the voice and data signals.

In a third aspect, the present invention provides a method
25 of signal transmission using a network as described herein.

Where signals are being transmitted along a polyphase (e.g. three phase) electricity power cable, the signal
30 propagation may be between any or all of the phases and ground. In a preferred embodiment the signal is injected between only one of the phases and ground, which also

provides unbalanced transmission characteristics and the cable behaves as a pseudo coaxial transmission line.

Where signals are being transmitted along a single phase electricity distribution service cable a pseudo-coaxial effect may also be obtained. Single phase cables may typically be either concentric or split-concentric. In the case of a split-concentric cable, means (such as a capacitive coupling between the parts of the split-concentric sheath) may be provided so that at the desired frequency the cable behaves as a standard concentric cable. Thus a pseudo-coaxial effect is achievable and the cable provides an unbalanced transmission characteristic.

The network conditioning unit preferably includes a low pass filter comprising a main inductor arranged between a mains electricity input and a mains electricity output and connected at each end thereof to a signal input/output line which is arranged in parallel to the mains electricity input and mains electricity output, the two connections including a first capacitor and a second capacitor each of a predetermined capacitance depending upon the portion of the frequency spectrum which is to be utilised for communications purposes.

In this arrangement the main inductor is operative to prevent communications signals from the signal input/output line from entering the domestic/industrial premises. This inductor is therefore preferably of a high inductance such as $10\mu\text{H}$ to $200\mu\text{H}$ for frequencies of 1MHz and above.

The first capacitor which connects the mains electricity input and the signal input/output line acts as a coupling capacitor to allow communication signals through from the signal input/output line whilst attenuating all low
5 frequency components at or about the main electricity supply frequency (ie., 50/60Hz).

The second capacitor arranged between the mains electricity output and the signal input/output line
10 provides a further attenuation of communication signals and is connected via the signal input/output line to ground.

In the event of failure of either the first or second
15 capacitor each such capacitor is preferably provided with a respective fuse arranged between the first or second capacitor and the signal input/output line. Furthermore an additional safety precaution can be incorporated by provision of a second inductor arranged between the
20 connections between the signal input/output line and the first and second capacitors. This inductor has no effect on communication frequency signals but will provide a path to ground if the first capacitor develops a fault, thereby allowing the first fuse to blow without allowing the power
25 frequency signal onto the signal input/output line.

The inductance of the main inductor depends upon the material of which it is made and the cross-section of the wire wound around the core. The 10pH inductance
30 previously specified is preferably a minimum and with use of better core material a higher inductance, for example of the order of 200pH, can be obtained. Alternatively, a

number of inductors connected in series could be used.

The coupling capacitor has a capacitance preferably in the range 0.01 to 0.50 μ F and the second capacitor linking the mains electricity output with the signal input/output line and ground has a capacitance preferably in the range of 0.001 to 0.50 μ F.

The second inductor arranged on the signal input/output line preferably has a minimum inductance of approximately 250 μ H. This inductor therefore has no effect on communication frequency signals on the signal input/output line. The conductor used to construct the 250 μ H inductor should be of sufficient cross-sectioned area to take fault current should the decoupling capacitor fail to short circuit condition.

Preferably, any spurious self resonance in the inductive or capacitive elements are avoided. As the lower cut off frequency of the conditioning unit is increased the minimum values of inductance and capacitance may be proportionally reduced.

In a preferred embodiment the filter is assembled in a screened box so as to provide a good earth and prevent radiation of the communication signals.

In a further aspect, the present invention provides an electricity distribution and/or power transmission network having a number of phases, said number being chosen from the list 1,2,4,5,6,7,8,9,n (where n is an integer greater than 9), but preferably having 1 or 2 phases, and

including input means for the input of a telecommunications signal having a carrier frequency greater than approximately 1MHz onto at least one of the phase conductors of the network and output means for
5 removing said telecommunications signal from at least one other phase conductor of the network.

In a further aspect, the present invention provides an unbalanced electricity distribution and/or power
10 transmission network at least a part of which comprises a clad cable, the network including input means for the input onto the network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications
15 signal from the network, said signal being transmissible along said part of the network having clad cable.

In a further aspect, the present invention provides a trunk and branch multipoint electricity distribution
20 and/or power transmission network including input means for the input onto the network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications signal from the network.

25
In a further aspect the present invention provides an electricity distribution and/or power transmission network at least part of which is external to a building, the network including input means for the input onto the
30 network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications signal from the

network, said signal being transmissible along said external part of the network.

Contrary to the teachings of the prior art, use of a carrier frequency of this magnitude is not impractical due to attenuation effects. This is because, at least higher frequencies, the cables of the power transmission and/or distribution network exhibit pseudo-coaxial characteristics and therefore attenuation is reduced.

10

In this way both speech and data signals can be transmitted at carrier frequencies of greater than approximately 1MHz, allowing for a larger available spectrum and greater transmission capacity. The carrier frequency may in fact be less than 1MHz i.e. 800kHz or even as low as 600kHz, but as it is reduced so is the bandwidth. A plurality of telecommunications signals may be provided, each having different carrier frequencies.

20 In a further aspect, the present invention provides a method of signal transmission including input of a telecommunications signal having a carrier frequency of greater than approximately 1MHz onto at least one phase conductor of an electricity power distribution and/or transmission network, and subsequent reception of the signal from at least one other phase conductor of the network, said network having a number of phases, said number being chosen from the list 1,2,4,5,6,7,8,9,n (where n is an integer greater than 9), but preferably
30 having 1 or 2 phases.

Any or all of the above aspects may include features

described elsewhere in this specification.

Embodiments of the present invention will now be described with reference to the accompanying drawings in which:

5

Fig. 1 is a schematic diagram of a part of a network in which aspects of the present invention may be used;

Fig. 2 is a schematic diagram of a first transmission
10 system for a network according to figure 1;

Fig. 3 is a schematic diagram of a second transmission system for a network according to figure 1;

15 Fig. 4 is a schematic diagram of a third transmission system for a network according to figure 1;

Fig. 5A is a cross section through a typical three phase cable;

20

Fig. 5B is a section through a typical coaxial cable;

Fig. 6 is a first embodiment of a network conditioning unit for use with the present invention;

25

Fig. 7 is a second embodiment of a network conditioning unit for use with the present invention;

Fig. 8 is a plan view of a network conditioning unit
30 according to figure 6;

Fig. 9 is a view of a circuit board for the network

conditioning unit of Fig. 8;

Fig. 10 is a schematic diagram of a network conditioning unit according to an aspect of the present invention;

5

Figs. 11a and 11b are schematic diagrams of network conditioning units as used with the present invention;

10 Figs. 12A, 12B and 12C show sectional views through a concentric, split-concentric and pseudo-concentric cable respectively;

Fig. 13 is a block diagram for a frequency converter according to an aspect of the present invention;

15

Fig. 14 is a circuit diagram for the frequency converter of figure 13;

20 Fig. 15 is a circuit diagram of a synthesiser circuit for the frequency converter of figure 14;

Fig. 16 is a circuit diagram for a power supply for a CT2 handset interface according to an aspect of the present invention;

25

Fig. 17 is a circuit diagram of a CT2 handset interface for use with the power supply of figure 16;

30 Fig. 18 is a circuit diagram of a base station line isolator circuit for use with the present invention; and

Fig. 19 is a schematic diagram showing the use of CDMA

transmission techniques according to an aspect of the present invention.

Fig. 1 shows generally a network 40. Mains electricity
5 enters the network from an 11kV transmission line 42, via
a transformer 44 and onto a 415V three phase network 46.
The 415V three phase network is supplied to a number of
locations, such as buildings 48. Each of these buildings
may receive only a single phase electricity supply or
10 alternatively may receive a three phase power supply.

Voice and data signals may be injected into the network
(or alternatively received from the network) at an
injection point 50, to be received by users in the
15 premises 48. In order to separate the voice and data
communication signals from the low frequency high
amplitude power signal each signal source and/or
destination is provided with a network conditioning unit
52 - shown in more detail in figure 11a. This network
20 conditioning unit includes a low pass filter for
separating out the two signals.

A further (high current) conditioning unit 51 - shown also
in figure 11b may be fitted between the electricity
25 distribution transformer 44 and the injection point 50 in
order to further remove transformer noise from the
conditioned network 40. The unit 51 is fitted with a high
current inductor.

30 Fig. 2 shows a portion of a three phase network 40 into
which and from which data signals may be transmitted and
received using the network conditioning units 52. The

cable of the network 40 is clad i.e. is surrounded by a sheath 41 e.g. along all or substantially all of its length. As an example, data signals could be transmitted onto the yellow phase of the network by network conditioning unit 52A i.e., the signal is applied between the yellow phase and earth as shown. The transmitted data may then be received by any or all of conditioning units 52B, 52C and 52D which are connected to the yellow, red and blue phases respectively. In other words transmitted data may be picked up on any phase of the cable, including the phases onto which the signals were not injected by the transmitting unit. This is due to the mutual capacitance between the phase conductors producing an effectively pseudo-coaxial nature of the three phase cable. As can be seen, data can be transmitted and received by each unit.

Each phase of the network 40 is shown to include a transformer 43. Typically this is effected by a single three phase transformer for all three phases, and not by three separate single phase transformers - although the latter may be possible.

Fig. 3 shows a portion of a three phase network 40 into which and from which data signals may be transmitted and received using four network conditioning units 52. As shown, the data signals are transmitted across two phases of the three phase network - in this case the red and blue phases.

If one or more phases are not in use (e.g. the yellow phase in Fig. 3), the non-used phases(s) may be terminated to provide an appropriate impedance. This may be done

- using an "L" circuit i.e. a series inductor with a shunter capacitor on the transformer side. This provides an optimum impedance and ensures that an RF signal which is coupled between e.g. the red and yellow phases, is not
5 shunted down by a low impedance transformer connection. This is particularly useful if there is insufficient inductive reactance at e.g. the yellow phase transformer connection point.
- 10 In Fig. 4 an alternative transmission system to Fig. 2 is shown, in which the data signals are transmitted across all three phases, i.e. blue, red and yellow, of the three phase network 40.
- 15 Fig. 13 is a schematic diagram showing an example of using one particular telephonic protocol (CT2) with a network according to the present invention. In normal use, CT2 equipment transmits and receives at a radio frequency of $866 \pm 2\text{MHz}$. The network is not generally suited for the
20 transmission of signals at this frequency, and so the system therefore incorporates frequency translation equipment to convert the CT2 signal to a frequency range of $8 \pm 2\text{MHz}$, in this example.
- 25 The equipment of figure 13 is based around a standard single line CT2 handset and base station pair. In order to allow the handset to provide the functions of a conventional wired telephone line at the subscriber's premises, baseband interface circuitry (see figs 16 and
30 17) is used in addition to the frequency conversion system.

The subscriber and substation equipment normally each contain the CT2 equipment plus three additional boards. These consist of the frequency converters and ready-built power supply (PSU) modules, which are identical in both
5 equipments, and the baseband interface boards which are different for each unit.

The frequency converter consists of five main parts: the synthesiser 200, down converter 202, up converter 204,
10 transmit/receive switch 206 and a band pass filter 208. Each of the up and down converter stages includes a RF band pass filter 210, 212 respectively, a mixer 214, 216 respectively, an amplifier 218, 220 respectively and a harmonic filter 222, 224 respectively.

15

In use, signals being transmitted from the conditioning unit 230 to the CT2 telephone equipment 232 will have their carrier frequency "up converted" by the up converter 204. Similarly, signals being transmitted from the CT2
20 equipment 232 to the conditioning unit (and then on to the network) will be "down converted" using down converter 202. The transmit/receive switch 206 operates to ensure that the appropriate frequency conversion occurs.

25 Figure 14 shows in more detail a circuit diagram of a suitable frequency converter.

Transmitted signals from the CT2 equipment are applied to the "TX IN" port, passed through a ceramic filter 24L to
30 eliminate spurious products, and reach the down-converter mixer via an attenuator and the mode switch IC5. The difference signal from the mixer is amplified by A1 and

passes to the transmit - receive switch IC6, which is controlled by the TXRXCO signal from the CT2 radio unit. From this switch the signal passes through the band filter, which consists of cascaded fifth-order Butterworth
5 high-pass and low-pass sections (L6-9, C48-53). These have cutoff frequencies of 6MHz and 10MHz respectively.

The filter output is passed through a 3dB attenuator, which serves to provide a reasonable match for the filter
10 even when the impedance match of the output load is poor, and emerges at the "8MHz RF to CU" port. This port is connected to the mains conditioning unit (CU) which couples the RF signal into the network.

15 Incoming signals from the conditioning unit pass back through the 6-10MHz band-pass filter and TX/RX switch IC6, emerge from port 'B' and are amplified by A2. The output of this amplifier is harmonic filtered and applied to the up-conversion mixer MX2. The output of this mixer is fed
20 to the input of the CT2 receiver via mode switch IC8 and a second 866MHz ceramic band-pass filter.

The purpose of the mode switches is to allow access to the 866MHz transmit and receive paths of the CT2 radio. This
25 enables a link to be set up at 866MHz (either by cable or through antennas) for test purposes.

The 866MHz signal paths are diverted away from the frequency converter proper by IC5 and IC8, and are
30 recombined by IC7 which acts as a transmit/receive switch controlled by the TXRXCO signal from the CT2 radio. In this manner the "866MHz RF" port (which is brought out to

an internal test socket) effectively replaces the original antenna port of the radio, and can be used in the same manner. The mode switches are controlled by logic signals from the on-board switch SW1, both true and complementary
5 signals being generated in order to simplify the routing of the RF tracks around the switch ICs. It should be noted that the mode control and 866MHz RF port are located internally to the equipment and do not play a part in its normal operation.

10

The 874.1MHz local oscillator is generated by the synthesiser circuit shown in figure 15. The VCO, which operates on the output frequency, is a Colpitts oscillator based around Q1. The frequency is determined by the
15 components around coaxial dielectric resonator DR1 and varactor diode D1. The output of the VCO is amplified and buffered by dual-gate MOSFET Q2, after which a signal is taken off to drive the prescaler IC3. The oscillator signal is then further amplified by IC2 and split two ways
20 by power divider PS1 to drive the up- and down- conversion mixers.

The control loop is formed by the synthesiser IC2, dual-modules prescaler IC3, and the loop filter based around
25 IC1 and associated components. The loop is of conventional Type II design, with a narrow bandwidth of about 150Hz. The frequency reference is provided by a 12.8MHz TCXO module driving the reference input of IC2.

30 Fig. 16 is a circuit diagram of a power supply for the interface board to interface between the CT2 handset and a basic telephony service.

The power supply provides three voltage rails:

- +12v -for audio circuitry (as supplied from PSU board)
- 5 +5v -for control logic
- +50v -for line interface

The incoming supply is +12v. This is regulated down to +5v by linear regulator IC6. The +50v supply is derived from the +12v rail by a push-pull forward converter based around IC1. Q1-2, D1-6, T1 and L1. The design is conventional, but an adjustment is provided for the oscillator frequency. This allows the frequency to be set so that its harmonics do not fall within the bandwidth of the CT2 second IF at 500kHz. This is achieved by using a frequency of 110kHz for the power converter, placing the 4th and 5th harmonics at 40kHz and 550kHz respectively.

Fig. 17 is a circuit diagram of an interface for the CT2 handset, including the line interface, audio interface and control logic.

The line interface is based around Q3-9, IC2 and their associated components, and handles both incoming and outgoing calls.

For outgoing calls, under quiescent conditions, REVERSE is low. When the subscriber's terminal goes off-hook, line current flows from the +50v supply via Q3, the subscriber's terminal and the constant-current sink formed by Q7 (whose base is held at +5v) and R15. A voltage is thereby developed across R15, and this performs three

functions. Firstly, the rising edge of this signal triggers IC3a, which enables IC4a for about 50ms. IC4a simulates operation of the CT2 handset's "Line" key and thus causes the CT2 system to initiate an outgoing call.

5 Secondly, it pulls one input of IC2c high, which forces REVERSE to stay low. Thirdly, it switches on Q9. This pulls the junction of R20 and R21 down to a low level, forward-biasing D8 and thus connecting C17 and the est of the audio circuitry (based around IC5) to the line.

10

When the subscriber's terminal goes back on-hook, line current ceases to flow and the voltage across R15 drops. The falling edge of this signal triggers IC3b and IC4b, which together simulate operation of the CT2 handset's

15 "Clear" key. This causes the CT2 system to clear down.

On receipt of an incoming call, the CT2 handset activates an internal open-drain buffer (which would normally drive the ringing transducer) which is connected to the RING

20 line and thereby discharges C10. This enables a 25Hz oscillator formed by IC2a,b and associated components.

Provided that the subscriber's terminal is on-hook, the output from this oscillator is gated to REVERSE. During the time that REVERSE is high, Q3 and Q7 are switched off, whilst Q4 and Q6 are enabled, reversing the polarity of the voltage applied to the line. In this manner the line is driven with a 25Hz square wave of 100Vpk-pk. Whilst this is lower than the ringing voltage supplied by a

30 normal public exchange line, it is nevertheless sufficient to cause the subscriber's terminal to register an incoming call. The ringing current is not sufficient to develop a

voltage across R15 which will operate IC2c or Q9. In fact the reason why Q9 and D8 are fitted is to ensure that this is so. If these components were not present then ringing current would flow in C17, which would not only heavily
5 load the 50V supply, but would also trigger the "off-hook" detection circuitry (IC2c, IC3) and thus cause malfunction of the system.

In order to simplify the system, no facility is provided
10 for decoding the dialled digits from the subscriber's terminal. It is therefore impossible to operate the present system in loop-disconnect mode. DTMF tones generated by the subscriber's terminal will be passed transparently through the audio channel once the line is
15 established.

Recall is achieved by IC4c and associated components. Since both wires of the line will normally have close to +50v on them, the 'earth recall' facility on the
20 subscriber's equipment will pull the recall line, and thus the control input of IC4c, up to a high level (rather than pulling the line voltage down to earth as would happen on a public exchange). IC4c is connected across the 'recall' key of the CT2 handset. It should be pointed out that the
25 "earth" wire (actually the RECALL line) is at a more negative voltage than the A and B wires of the line, rather than more positive as is normal practice on public exchange lines.

30 The hybrid is formed by IC5 and associated components, and is coupled to the line via C17. Output from the CT2 handset is applied to the non-inverting input of IC5a,

which is configured as a unity-gain buffer. The output of IC5a drives the line via the balancing impedance Z_b , which is formed by C18, C19 and R28-30.

- 5 IC5b acts as a conventional differential amplifier. If the impedance presented by the line is the same as Z_b , then any signals arising from the output of IC5a appear purely in common mode at the inputs of IC5b and thus do not appear at the output of the latter. Incoming signals
10 from the line, however, are applied only to the non-inverting input of IC5b and are passed on with a gain of +2. The output from IC5b forms the input signal for the CT2 handset.
- 15 Fig. 18 is a circuit diagram of an isolation interface for use between a base station and sub-station equipment. It is necessary to isolate the base station from the PSTN line to allow connection to mains earth as the line interface is not isolated from the RF part in the original
20 design. This is accomplished by means of a small add-on board which takes over the hybrid and line switching functions.

- The circuit diagram of this board is shown in figure 6.
- 25 After passing through protection network L1-L2-VDR (transferred from original GPT base station) the line current is rectified by BR1 to make the circuit independent of line polarity. Q1 provides the line switching function and is driven from the base station's
30 control logic via IL2 and R2, R3 and D2. The earth recall facility is provided by Q2 and associated components, driven via IL3. Conveniently, these functions are both

controlled using opto-isolators in the original circuit, although these were used for level-shifting rather than isolation. It should be noted that the output transistors of IL2 and IL3 have to be capable of withstanding the peak
5 ringing voltage in the 'off' state, so high voltage types are specified here.

Ringing current is rectified by BR2 and drives IL1 via R1 and D1 - the latter being present to prevent high level
10 audio signals from getting through to IL1.

As there is no facility for loop-disconnect dialling in this system, no masking circuitry is needed either for the audio path or the ringing detector. This would otherwise
15 by required to prevent the loop-disconnect pulses from operating the ringing detector or overloading the audio channel.

The remaining circuitry provides the audio path. Signals
20 to be transmitted are applied to Darlington Q3-Q4 via isolating transformer T1 and associated bias components. This pair of transistors in conjunction with R13 and R14 form a constant-current source which is modulated by the outgoing audio signal. The resulting signal splits via R8
25 and R9 between the line and the balance impedance formed by C3-5 and R10-12. If the line impedance is equal to the balance impedance, the signal voltages across R8 and R9 are equal and opposite and no signal appears across T2. This arrangement thereby provides sidetone cancellation.
30 Incoming signals from the line however, do develop a signal in T2 which is output to the CT2 base station.

Another particularly suitable communication protocol for use with the present invention is CDMA, and fig. 19 is a graph of voltage against frequency for an exemplary CDMA signal according to the present invention. Line 400
5 designates the basic CDMA signal which is a relatively broadband low power signal. However, according to one aspect of the present invention, additional signals can also be transmitted at the same time. Examples of such additional signals are designated 402, 404 and 406, and it
10 will be seen from fig. 19 that such additional signals are relatively narrow band signals.

The narrow band signals will interfere with the CDMA signal in the regions covered by those narrow band
15 signals, but the data included in the CDMA signal may still be recoverable from the other parts of the frequency spectrum of the CDMA signal. Thus additional data signals (402, 404 and 406) can be included along side the basic CDMA signal 400.

20

Fig. 5A shows a simplified cross section of a three phase power cable 54, including red phase 56, yellow phase 58, and blue phase 60. Data signals are transmitted between blue phase 60 and earth 62, and are injected into the
25 network via network conditioning unit 52. At high frequencies, the mutual capacitance between the phases effectively produces a short circuit. Therefore, such a transmission system gives a pseudo-coaxial characteristic, roughly equivalent to the coaxial cable shown in Fig. 5B.
30 The mutual capacitance between any two of the phases in the three phase cable is shown schematically as 64 in Fig. 5A - similar mutual capacitance exists between other parts

of phases.

The basic elements of a network conditioning unit 101 according to one aspect of the present invention are illustrated in Figs. 11a and 11b. Fig. 11a shows conditioning units as designated 52 and 51 in fig. 1 respectively. The conditioning unit can be considered to be equivalent to a low pass filter 100 and a coupling capacitor element 102 (which can be considered to be a high pass filter element).

The low pass filter element 100 allows mains power to be supplied from the distribution network to a consumer whilst preventing high frequency communication signals from entering the consumers premises. A coupling capacitor, or high pass filter element, 102 is provided to couple the high frequency communication signals onto the distribution network whilst preventing the mains power from entering the communications apparatus.

The conditioning unit components may be fitted into e.g an electricity meter case located in a consumer's premises, or possibly may be set into a compartment at the rear of such a meter. Alternatively the necessary components may be located in e.g. a customer's high rupturing capacity (HRC) fuse or cut-out unit.

Referring to Fig. 6, an embodiment of a conditioning unit (essentially a filter) according to an aspect of the invention is indicated generally by the reference numeral 10 and is connected between a mains electricity input 12 and a mains electricity output 14. A signal input/output

line 16 is also connected into the filter. The mains power line is a standard 50Hz mains electricity power supply providing a domestic electricity power source of 240v at a maximum current of 100 amps for normal usage.

5

The filter 10 is assembled into a metal box which prevents radiation of the communication signals to externally located appliances and which provides a connection 18 to earth for the signal input/output line 16. The filter 10 includes a first or main inductor 20 formed e.g. of 16mm² wire wound on a 10mm diameter, 200mm long ferrite rod with 30 turns of wire therearound. This provides an inductance of approximately 50μH. This may be a minimum for the signal characteristics utilised. The use of better materials or a plurality of series inductors would increase the inductance of the inductor up to, for example, approximately 200μH.

Each end of the main inductor 20 is provided with a connection to the signal input/output line 16. A first connection 22 between the mains electricity input 12 and signal input/output line 16 comprises a first or coupling capacitor 24 having a capacitance of between 0.01 and 0.50μF, and preferably around 0.1μF. This coupling capacitor 24 is connected to a first fuse 26 which is arranged to blow in the event of failure or a fault developing in capacitor 24.

A second connection 28 includes a second capacitor 30 having a capacitance of between 0.001 and 0.50μF, preferably around 0.1μF. This capacitor provides further attenuation of the communication signals by shorting to

the earth or ground 18. A second fuse 32 is provided to blow if a fault develops in the second capacitor 30, thereby preventing further unit damage.

- 5 The signal input/output line 16 is connected to a second inductor 34 having an inductance of approximately 250 μ H minimum. This inductor is provided as a damage limiter in the event of failure of the coupling capacitor 24. In the event of such failure this inductor provides a path to the
- 10 ground 18 for the 50Hz mains electricity power frequency, thereby blowing fuse 26. The inductor has no effect on the communication frequency signals present on the signal input/output line 16.
- 15 Fig. 7 shows a second embodiment of a filter according to an aspect of the present invention. The filter 70 includes a pair of inductors L1, L2 arranged in series between a mains electricity input 72 and a mains electricity output 74. A preferred value for L1 and L2 is
- 20 approximately 16 μ H. Connected between the RF input line 80 and the mains input 72 is a first fuse F1 and capacitor C1, and connected between the RF input 80 and ground is a third inductor L3, which acts as an RF choke and has a typical value of 250 μ H.
- 25 Connected in a similar fashion between the connection point of L1 and L2 and ground is a second fuse F2 and second capacitor C2. Connected between the mains electricity output 74 and ground is a third fuse F3 and
- 30 third capacitor C3. A typical value for the capacitors is around 0.1 μ F and for the fuses approximately 5 amps HRC (high rupturing capacity).

The values given for these components are exemplary only, and different preferred values will be appropriate for other design frequencies.

5

Turning to Fig. 8 a typical housing arrangement for a network conditioning unit according to an embodiment of the present invention is shown. The main inductors L1 and L2 are housed within a shielding box 90. Various
10 connections are shown, including a communication interface port 92 to which a user's communication equipment would normally be connected. However, as shown in Fig. 8, this port may be terminated in an impedance matching port terminator 94.

15

Fig. 9 shows a circuit board 96 which fits inside the unit 90 of figure 8 and houses the rest of the circuitry for the network conditioning unit of figure 7. Connections A, B, C, D and E are shown which connect to the appropriate
20 points of the box shown in figure 8.

Fig. 10 is a schematic representation of a network conditioning unit 52, showing the various building blocks 80-86 of the network conditioning element. To design a
25 suitable network conditioning unit, the circuits represented by blocks 81 and 86 should be high-impedance elements over the required communications frequency spectrum (eg. 1MHz and above) and low impedance elements at frequency of mains electricity supply (ie. 50/60HZ)
30 i.e. these elements are inductors. Similarly blocks 80 and 82 should be low impedance coupling elements over the required communications frequency spectrum and high

impedance isolating elements at the frequency of the mains electricity supply ie. they are capacitors.

- 5 HRC fault current limiting fusible safety links (84 and 85) are provided in series with elements 80 and 82. An additional impedance matching network 83 may be included for connection to a communications port. This element may be external to the network conditioning unit 52.
- 10 The optimum values of items 81, 80, 82 and 86 will be dependant upon factors including:-
- a) The required frequency range over which the network is to be conditioned.
 - 15 b) The unit length of the network which is to be conditioned.
 - c) The number and types of loads which may be encountered
 - 20 on the network.
 - d) The characteristic impedance of the network phase conductors with respect to earth ie. conductor outer electrical sheath.
 - 25 e) The impedance of the communications interface devices.

The network conditioning unit may be filled with air, inert gas, resin compound or oil depending upon the

30 location and load and/or fault current ratings of the conditioning unit. Also it may be, for example, sited indoors, pole mounted, buried underground or inserted in

street lamp columns.

Similarly items 81 and 86 may comprise a number of individual inductors in series, and if no interconnection is required, for example, on a street light, items 84, 80, 83 and 86 may be omitted.

Items 80 and 82 may comprise of a number of capacitors in series and/or parallel configuration depending upon working voltages encountered ie. 240, 415, 11kV, 33kV etc. Alternatively, or additionally, items 80 and 82 may comprise of two or more capacitors in parallel in order to overcome, for example, deficiencies in capacitor design when conditioning a network over a relatively wide frequency range, for example 50 MHZ to 500 MHZ.

Furthermore, items 81, 85 and 82 of the network conditioning unit may be cascaded if required. In a typical design, the greater the number of cascaded elements the sharper will be the roll off response of the filter and the greater its attenuation.

Figs. 12A, 12B and 12C show sectional views through a single phase concentric, split-concentric and "pseudo"-concentric cables respectively. A typical concentric single phase cable (as illustrated in Fig. 12A) consists of a central metallic conductor core (typically aluminium) 110 surrounded by an insulating layer 112 (typically PVC). Around the insulating layer 112 are laid a plurality of metallic conductors 114 (typically copper) over which lies an insulating and protective sheath 116 (typically PVC). In use the neutral and earth are combined in the outer

sheath of metallic conductors 114.

A split-concentric cable (as illustrated in Fig. 12B) is similar to the concentric cable except that the outer
5 layer of metallic conductors 114 is split into two portions - e.g. an upper portion 115 and a lower portion 117. These portions are divided by insulators 118, 120 and in use the neutral and earth are split so that one portion of the outer metallic sheath carries only one of
10 them.

In order to maintain a pseudo-coaxial effect in the split-concentric service cables at the desired transmission frequencies (e.g. above 1MHz) one or more capacitors 122
15 may be connected between the upper and lower portions 115, 117 of the outer metallic sheath 114. These capacitor(s) may be fitted e.g. at the termination and/or conditioning points of the cable.

20 It will be seen from the foregoing that the invention provides a simple filter effectively separating signals having a frequency spectrum indicative of radio communication signals from those of standard mains electricity power supply without significant loss of power
25 or quality in either signal. Thus the electricity distribution and/or transmission network(s) can be used for both the provision of electricity supply and the propagation of telecommunications signals, which may be analogue and/or digital in format.

30

The use of a filter according to the invention at each consumer supply point in a low voltage electricity

distribution network provides a conditioned network
suitable for the transmission of high frequency
communication signals together with the distribution of
50Hz, 240v single and 415v, three phase electricity
5 supplies. The provision of such a conditioned network
constitutes a further aspect of the invention.

The invention is not confined to the foregoing details and
variations may be made thereto within the scope of the
invention.

CLAIMS:

1. An electricity distribution and/or power transmission
5 network at least part of which is external to a building,
the network including input means for the
input onto the network of a telecommunications signal
having a carrier frequency greater than approximately 1MHz
and output means for removing said telecommunications
10 signal from the network, said signal being transmissible
along said external part of the network, wherein the
network is adapted to transmit said signal using
frequency, time and/or code division multiplexing
techniques.
- 15
2. A network according to claim 1 wherein the network is
adapted to transmit said signal using Code Division
Multiple Access (CDMA) communication techniques.
- 20
3. A network according to claim 1 or claim 2 wherein the
network adapted to transmit said signal using one or more
of the following cordless telephony techniques:
- 25
- R-CDMA (Rockwell-Code Division Multiple Access),
telephony standards CTO, CT1 and CT2, AMPS, DECT (Digital
European Cordless Telephone Standard), IS-54, IS-95, GSM,
Q-CDMA, UD-PCS, PHS, PACS, TACS, ENTACS, NMT450, NMT900,
30 C-450, RTMS, Radicom 2000, NTJ, JTACS & NTACS, DCS 1800,
etc.

4. A network according to any one of the above claims wherein the carrier frequency is between approximately 1-60MHz.
- 5 5. A network according to any one of the above claims wherein signal propagation is between at least one of the phase conductors of the network and earth.
6. Communications apparatus adapted for use with a mains
10 electricity transmission and/or distribution network, including signal transmission and/or reception means, and frequency conversion means for converting the frequency of a signal transmitted or received by signal transmission and/or reception means to a frequency which facilitates
15 improved propagation of the signal on the network.
7. Communications apparatus according to claim 6 wherein said signal transmission and/or reception means is adapted to operate according to a telephony standard which uses a
20 relatively high carrier frequency, and said frequency conversion means is usable to convert a signal having a relatively high carrier frequency to a signal having a lower carrier frequency.
- 25 8. Communications apparatus according to claim 7 wherein said signal transmission and/or reception means is adapted to operate according to the CT2 or CDMA telephone standards.
- 30 9. Communications apparatus according to claim 7 or claim 8 wherein said frequency conversion means is usable to convert the carrier frequency of said signal to between

1 and 60 MHZ.

10. Communications apparatus according to any one of
claims 6 to 9 wherein said signal transmission and/or
5 reception means comprises telephone equipment.

11. Communications apparatus according to any one of
claims 6 to 10 connected to an electricity power
distribution and/or transmission network.

10

12. Communications apparatus according to claim 11
wherein said network is a network according to any one of
claims 1 to 5.

15 13. Use of a communications apparatus with an electricity
distribution and/or power transmission network, the
apparatus including signal transmission and/or reception
means, and frequency conversion means for converting the
frequency of a signal transmitted or received by signal
20 transmission and/or reception means to a frequency which
facilitates improved propagation of the signal on the
network.

14. A method of signal transmission including input of a
25 telecommunications signal having a carrier frequency of
greater than approximately 1MHz onto an electricity power
distribution and/or transmission network at least part of
which is external to a building and subsequent reception
of the signal, said signal being transmitted along said
30 external part of the network, wherein said signal is
transmitted using frequency, time and/or code division
multiplexing techniques.

15. Use of telecommunications apparatus for transmission or reception of a telecommunications signal having a carrier frequency greater than approximately 1MHz on a network according to any one of claims 1 to 5.

5

16. An electricity distribution and/or power transmission network substantially as herein described with reference to the accompanying drawings.

10 17. Communications apparatus substantially as herein described with reference to the accompanying drawings.

18. A method of signal transmission substantially as herein described with reference to the accompanying
15 drawings.

19. An electricity distribution and/or power transmission network having a number of phases, said number being chosen from the list 1,2,4,5,6,7,8,9,n (where n is an
20 integer greater than 9), including input means for the input of a telecommunications signal having a carrier frequency greater than approximately 1MHz onto at least one of the phase conductors of the network and output means for removing said telecommunications signal from at
25 least one other phase conductor of the network.


20. An unbalanced electricity distribution and/or power transmission network at least a part of which comprises a clad cable, the network including input means for the
30 input onto the network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications


signal from the network, said signal being transmissible along said part of the network having clad cable.

21. A trunk and branch multipoint electricity
5 distribution and/or power transmission network including input means for the input onto the network of a telecommunications signal having a carrier frequency greater than approximately 1MHz and output means for removing said telecommunications signal from the network.
10
22. An electricity distribution and/or power transmission network at least part of which is external to a building, the network including input means for the input onto the network of a telecommunications signal having a carrier
15 frequency greater than approximately 1MHz and output means for removing said telecommunications signal from the network, said signal being transmissible along said external part of the network.
- 20 23. A method of signal transmission including input of a telecommunications signal having a carrier frequency of greater than approximately 1MHz onto at least one phase conductor of an electricity power distribution and/or transmission network, and subsequent reception of the
25 signal from at least one other phase conductor of the network, said network having a number of phases, said number being chosen from the list 1, 2, 4, 5, 6, 7, 8, 9... (where n is an integer greater than 9).

1/20


FIG. 1






3/20

FIG.3



4/20

FIG.4






FIG.5 A






FIG.5 B

6/20


FIG. 6



7/20




8/20



9/20

FIG.9



10/20




FIG.10

11/20




FIG 1a

12/20




FIG 11 b

13/20




FIG 12A




FIG 12B




FIG 12C

14/20





FIG 13

15/20



Note:
SW1 open for 6MHz (normal) mode
SW1 closed for 66MHz (test) mode

16/20




FIG 15

18/20




FIG 17

19/20




FIG 18




FIG 19

INTERNATIONAL SEARCH REPORT

International Application No

PCT/GB 95/00894

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H04B3/54

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 6 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO,A,93 07693 (PHONEX CORPORATION) 15 April 1993	1-4,6-23
Y	see page 1, line 35 - page 2, line 3 see page 3, line 15 - line 26 see page 3, line 31 - page 4, line 3 see page 6, line 32 - line 38 see page 12, line 33 - page 13, line 3; figure 4	5
Y	FR,A,2 326 087 (ZELLWEGER USTER S.A.) 22 April 1977 see page 2, line 25 - line 31	5
A	PATENT ABSTRACTS OF JAPAN vol. 11 no. 341 (E-554), 7 November 1987 & JP,A,62 120735 (NEC HOME ELECTRONICS LTD) 2 June 1987, see abstract	1,14,22

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- "&" document member of the same patent family

Date of the actual completion of the international search

29 June 1995

Date of mailing of the international search report

18.07.95

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+ 31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+ 31-70) 340-3016

Authorized officer

Bossen, M

INTERNATIONAL SEARCH REPORT

Information on patent family members

Patent Application No

PCT/GB 95/00894

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO-A-9307693	15-04-93	US-A- 5319634	07-06-94
		AU-A- 2861392	03-05-93
		BR-A- 9206605	28-03-95
		CA-A- 2119378	15-04-93
		EP-A- 0607304	27-07-94
		JP-T- 7501663	16-02-95
FR-A-2326087	22-04-77	CH-A- 589979	29-07-77
		DE-A- 2623699	31-03-77
		JP-A- 52040909	30-03-77
		NL-A- 7607898	29-03-77
		US-A- 4097692	27-06-78

15m

THIS PAGE BLANK (USPTO)

THIS PAGE BLANK (USPTO)